

CCTV Security Camera 4 Pack

The complete all purpose surveillance solution.
Total safety for the home, office or retail space



- 2 x C-500R Professional CCD Cameras
- 2 x Bulldog Cam Professional CCD Cameras
- High resolution CCD video images
- Connects easily to DVR, Quad Processor, 4 Camera Switcher or TV
- Safeguard loved ones, protect property & deter thieves





CCTV Security Camera 4 Pack

The complete all Purpose surveillance solution. Total safety for the home, office or retail space.

Ideal for:



Retail Stores



Warehouses



Offices



Home

Technical Specifications

Bulldog Cam

Sensor: 1/4" Sharp CCD Image Sensor
 Image Sensor Pixels: PAL: 500(H) x 582(V)
 NTSC: 510(H) x 492(V)
 Video Signal: NTSC (USA)
 PAL (AU, UK, EU)
 Sync. System: Internal
 Horizontal Resolution: 420TV Line
 Minimum Illumination: 1.0Lux/F1.2; 0Lux (IR ON)
 S/N Ratio: More than 48dB (AGC off)
 Electronic Shutter: PAL: 1/50~1/100,000sec
 NTSC: 1/60~1/100,000sec
 Video Output: 1Vp-p75Ohm
 IR Distance: 15m Light below 10Lux,
 CDS automatically open
 IR-LED: 12pcs
 Dimension (mm): 53.5(D) x 76.5(L) x 130(H)
 Weight (g): Approx 450
 Operation Temperature: 0C~50C
 32F~122F

C-500R Camera

Sensor: 1/4" Sharp CCD Image Sensor
 Image Sensor Pixels: PAL: 512(H) x 582(V)
 NTSC: 512(H) x 492(V)
 Video Signal: NTSC (USA)
 PAL (AU, UK, EU)
 Sync. System: Internal

Horizontal Resolution: 400TV Line
 Minimum Illumination: 1.5Lux/F1.2
 S/N Ratio: >48dB
 Electronic Shutter: 1/50(1/60)~1/100,000sec
 Lens Mount: C/CS
 Video Output: <1.2Vp-p/75Ohm
 Backlight Compensation: On/Off
 Iris Control: Video or DC
 White Balance: Auto
 Dimensions (mm): 119(L) x 59(W) x 52(H)
 Weight (g): 236
 Operation Temperature: 0C~50C
 32F~122F
 Gamma Correction: >0.45

Package Contents

- 2 x C-500R CCD Camera & Camera Stand
- 2 x Bulldog Cam & Stand
- 12 Volt Power Adaptors to suit cameras
- 1 x 3.5-8mm Manual Vari-Focal Lens (For C-500R)
- 1 x 4mm Fixed Lens (For C-500R)
- BNC (F) to BNC (F) and BNC to RCA Adaptors
- 5 x 18m Cable
- Instruction Manual



www.swannsecurity.com

Please note that the information contained within this document is subject to change without notification.